arXiv:1005.2743v1 [math.SP] 16 May 2010

RESONANCE SPECTRUM FOR ONE-DIMENSIONAL LAYERED MEDIA

ALEXEI IANTCHENKO

ABSTRACT. We consider the "weighted" operator $P_k = -\partial_x a(x)\partial_x$ on the line with a step-like coefficient which appears when propagation of waves thorough a finite slab of a periodic medium is studied. The medium is transparent at certain resonant frequencies which are related to the complex resonance spectrum of P_k.

If the coefficient is periodic on a finite interval (locally periodic) with k identical cells then the resonance spectrum of P_k has band structure. In the present paper we study a transition to semi-infinite medium by taking the limit $k \to \infty$. The bands of resonances in the complex lower half plane are localized below the band spectrum of the corresponding periodic problem ($k = \infty$) with $k-1$ or k resonances in each band. We prove that as $k \to \infty$ the resonance spectrum converges to the real axis.

1. INTRODUCTION

In the present paper we consider operator $P_k = -\partial_x a_k(x)\partial_x$ on the line with step-like coefficient a_k which is periodic on a finite interval defined as follows:

$$a_k(x) = a(x), \text{ for } x \in [0,k]; \ a_k(x) = \frac{1}{b_1^2}, \text{ for } x \notin [0,k], \tag{1}$$

where $a(x)$ is $1-$periodic function equal to

$$a_0(x) = \begin{cases} b_2^{-2} & \text{for } x \in [0, x_2) \\ b_1^{-2} & \text{for } x \in [x_2, 1) \end{cases} \tag{2}$$

for $x \in [0,1)$. Here $b_{1,2} > 0$ and $0 < x_2 < 1$. Equation

$$P_k\psi = -\partial_x a_k(x)\partial_x\psi(x) = \lambda^2\psi$$

appears when the propagation of waves through a finite slab of a periodic medium is studied. Such systems are also called finite or locally periodic media (for revue see [6]).

When k is large then the properties of medium is close to an infinite periodic problem in a sense that we are going to discuss in the present paper.

We denote $P = -\partial_x a(x)\partial_x$ the pure periodic operator, where $a(x)$ is $1-$periodic function equal to a_0 for $x \in [0,1)$ as in (2). Then the Floquet theory shows the existence of a pair of the quasi-periodic solutions $\psi_\pm$ of the equation $-\partial_x a(x)\partial_x\psi_\pm = \lambda^2\psi_\pm$,

$$\psi^\pm(\lambda, x+1) = e^{\pm i\theta}\psi^\pm(\lambda, x),$$

such that $\psi^\pm \in L^2(\mathbb{R}_\pm)$ for $\operatorname{Im}\lambda > 0$. Here $\theta = \theta(\lambda)$ is the Bloch phase. We denote

$$F(\lambda) = \frac{\rho+1}{2}\cos\{\lambda(x_2b_2 + (1-x_2)b_1)\} - \frac{\rho-1}{2}\cos\{\lambda(x_2b_2 - (1-x_2)b_1)\} \tag{3}$$

Date: May 18, 2010.

2000 *Mathematics Subject Classification.* 47A10, 47A40, 81Q10.

Key words and phrases. One-dimensional, layered, truncated periodic, scattering resonances.

the Lyaponov function for P (see Section 2.1). Here

$$\rho = \frac{b_1^2 + b_2^2}{2b_1 b_2}.$$

The spectrum of the operator P has band structure with allowed zones defined as follows:

$$\lambda \in \sigma(P) \ \Leftrightarrow \ |F(\lambda)|^2 < 1, \ \lambda \in \mathbb{R} \tag{4}$$

(see [4] and Section 4). The band edges are given by solutions of $F(\lambda) = \pm 1$.

The relation between the Bloch phase θ and the spectral parameter λ is called dispersion relation:

$$\cos\theta(\lambda) = F(\lambda).$$

Since the coefficient $a(x)$ is constant equal to $1/b_1^2$ outside a finite region, we are here concerned with a scattering problem.

We shall denote the reflection and transmission coefficients for the operator P_k by r_k and t_k, respectively:

$$P_k\psi = \lambda^2\psi, \ \psi = e^{i\lambda b_1 x} + r_k e^{-i\lambda b_1 x}, \ x < 0; \ \psi = t_k e^{i\lambda b_1 x}, \ x > k.$$

Following the ideas in [7] we consider a transition to semi-infinite periodic materials by taking the limit $k \to \infty$ of the reflection coefficient r_k for P_k.

The limiting operator

$$P_\infty \psi = -\partial_x a_\infty(x) \partial_x \psi(x)$$

corresponds to the case of such a long slab that it can be considered as half infinite.

In the case of the operator P_∞, the solution ψ of the scattering problem is defined as the solution of the equation $P_\infty\psi = \lambda^2\psi$, such that

$$\psi = e^{i\lambda b_1 x} + r e^{-i\lambda b_1 x}, \ x < 0; \ \psi = c\psi^+(\lambda, x), \ x > 0, \tag{5}$$

with some $r = r(\lambda)$, $c = c(\lambda)$.

As in [7] we have that the reflection coefficients $r_k(\lambda)$ and $r(\lambda)$ are analytic in the upper half plane $\mathbb{C}_+ = \{\lambda : \ \operatorname{Im}\lambda > 0\}$ and continuous in $\overline{\mathbb{C}}_+$, and $r_k(\lambda) \to r(\lambda)$ when $k \to \infty$ and $\lambda \in \mathbb{C}_+$. When λ is real, $r_k(\lambda)$ converges to $r(\lambda)$ in the weak sense (see Theorem 2, Section 2.2).

Numerical calculation shows that in each allowed zone of $\sigma(P)$ there are in general $k-1$ frequencies λ_j where the transmission probability is one: $|t_k(\lambda_j)|^2 = 1, \ j = 1, \dots, k-1$, and the medium is perfectly transparent: $|r_k(\lambda_j)|^2 = 0$. There exist an additional frequency λ_0 when the medium consisting of only one unit cell is transparent and then $|t_n(\lambda_0)|^2 = 1$ for all $n = 1, 2, \dots, k$. The pics in the transmission probability are related to the complex resonances close to the real axis.

We make the following definition.

The operator P_k defined from $\{u \in H^1(\mathbb{R}), \ a\partial_x u \in H^1(\mathbb{R})\}$ to $L^2(\mathbb{R})$ is self-adjoint. For $\operatorname{Im}\lambda > 0$, we call $R_k(\lambda)v = (-\partial_x a(x)\partial_x - \lambda^2)^{-1}v$ the resolvent of P_k. For any $k = 1, 2, \dots,$ the operator-valued function

$$R_k(\lambda) : \ L^2_{\mathrm{comp}}(\mathbb{R}) \mapsto L^2_{\mathrm{loc}}(\mathbb{R})$$

can be continued to the lower complex half-plane $\mathbb{C}_-$ as a meromorphic function of $\lambda \in \mathbb{C}$ and it has no poles for $\operatorname{Im}\lambda \geq -\epsilon_k, \ \lambda \neq 0$, with $\epsilon_k > 0$ positive constant dependent on k (see Section 4).

The poles of the $R_k(\lambda)$ in $\mathbb{C}_-$ are called *resonances* or *scattering poles.* We denote the set of resonances $\operatorname{Res}(P_k)$.

Using the explicit construction of the resolvent in [4] the poles are calculated numerically. Some examples are presented in Section A, figures (1), (2) and (3). We summarize the properties of $\operatorname{Res}(P_k)$ in the following Theorem.

Theorem 1. *We consider the finite periodic P_k and periodic P operators generated by the same unit cell given in (2). Let $\operatorname{Res}(P_k) \subset \mathbb{C}_-$ denote the resonance spectrum for the finite periodic system with $k = 2, 3\dots$ identical cells and $\sigma(P) \subset \mathbb{R}$ denote the band spectrum for P given by (4).*

The resonance spectrum for the finitely periodic system has band structure related to the bands of the real spectrum for the pure periodic problem as follows:
1) *The resonance spectrum of P_k has band structure. Resonances are localized below the bands of the real spectrum of P :*

$$\lambda \in \operatorname{Res}(P_k) \quad \Rightarrow \quad \operatorname{Re}(\lambda) \text{ satisfies } (4) \quad \Leftrightarrow \quad \operatorname{Re}(\lambda) \in \sigma(P_\infty).$$

Each resonance band of P_k consists of $k-1$ resonances $\lambda_1, \dots, \lambda_k - 1$ and eventually an additional resonance with real part $\operatorname{Re}\lambda = \lambda_0 = \pi m/x_2 b_2$, $m \in \mathbb{Z}$, such that $|t_1(\lambda_0)|^2 = 1$, the one-cell medium is "perfectly transparent" at frequency λ_0.
2) *If the condition*

$$b_2 x_2 = b_1(1 - x_2) \;\Leftrightarrow\; \frac{b_1}{x_2} = \frac{b_2}{1 - x_2}. \tag{6}$$

is satisfied then $\lambda_0 = \pi m/x_2 b_2$, $m \in \mathbb{Z}$, is the degenerate band edge (two bands has common edge at λ_0). The resonance spectrum $\operatorname{Res}(P_k)$, $k = 1, 2, 3, \dots,$ is periodic with the period $T = \frac{\pi}{b_2 x_2}$.
3) *As $k \to \infty$ then the resonance spectrum of P_k approaches the real axis.*

In the present paper we motivate these numerical results.

The band structure of the resonance spectrum for a finitely periodic system and its relation to the band spectrum of the correspondent periodic problem is well-known in physical literature (see [1]).

We say that $\operatorname{Res}(P_k)$ is periodic if there exists $T > 0$, period, such that

$$\operatorname{Res}(P_k) \cap ([q + Tn, p + Tn] - i\mathbb{R}) = \operatorname{Res}(P_k) \cap ([q + Tm, p + Tm] - i\mathbb{R})$$

for any $q < p$ and $n, m \in \mathbb{Z}$. This property follows directly from the equations defining the resonances in Section (4.2) if condition (6) is satisfied.

A special property of the operator $P = -\partial_x a(x)\partial_x$ with step-like periodic coefficient $a(x)$ is that the coefficients $(r \pm 1)$ in the dispersion relation

$$2\cos\theta(\lambda) = (\rho + 1)\cos\{\lambda(x_2 b_2 + (1 - x_2)b_1)\} - (\rho - 1)\cos\{\lambda(x_2 b_2 - (1 - x_2)b_1)\} \tag{7}$$

are independent of the spectral parameter λ. Formula (7) implies that the band spectrum is periodic if the profile of a verifies (6).

The third part of the Theorem is proved in Section 6.

The convergence of the resonances for a finitely periodic system with k cells to the bands of real spectrum for the periodic problem as $k \to \infty$ was discussed by F. Barra and P. Gaspard in [3] in the case of Schrödinger equation.

In our proof we use representations for the reflection and transmission coefficients r_k, t_k for a finite slab of periodic medium as in the recent paper of Molchanov and Vainberg [7]. The authors considered transition of truncated medium described by the 1−D Schrödinger operator to semi-infinite periodic materials. By relating the reflection coefficients to the resolvent of P_k we show explicitly that the resonances correspond to the poles of the analytic continuation of $r_k(\lambda)$ to $\mathbb{C}_-$. Then we consider the limit of the poles of $r_k(\lambda)$, as $k \to \infty$.

Note that for $\lambda \in \mathbb{R}$ the reflection coefficient r_{k+1} for $k + 1$ cells medium is related to r_k for k cells medium via $r_{k+1} = f_\lambda(r_k)$, where f_λ is a linear-fractional automorphism of the unit disk. By considering the fixed point of f_λ we get a new proof of the convergence of $r_k(\lambda)$ to $r(\lambda)$ when

λ belongs to the spectral gapes and non-degenerate band edges for the operator P (see Section 7).

The structure of the paper is the following:
In Section 2 we recall some well-known facts concerning spectral problem for weighted Sturm-Liouville operators (see [2]) and consider scattering by a finite slab of a periodic medium. We follow [7] with minor changes due to the special form of operator P_k. We recall exact formulas for the the reflection and transmission coefficients using the iteration of the monodromy matrix. We recall also the result of [7] on a transition to semi-infinite periodic material (limit $k \to \infty$). In Section 3 we give explicit expression for the monodromy matrix of P_k. In Section 4 we recall the iterative procedure used in [4] for construction of the resolvent R_k and define resonances. In Section 5 the reflection coefficient r_k is expressed using the iteration formulas of [4] and we show that the poles of $R_k(\lambda)$ and the poles of $r_k(\lambda)$, $\lambda \in \mathbb{C}_-$, coincide. In Section 6 we prove the convergence of $\mathrm{Res}\,(P_k)$ to the real axis. In Section 7 we discuss the convergence of $r_k(\lambda)$, $k \to \infty$, for $\lambda \in \mathbb{R}$ by considering the limit of a sequence of linear-fractional automorphisms on the unit disk. In Appendix A we present numerical examples.

Acknowledgements. The author would like to thank Maciej Zworski for suggesting to look at the problem considered in the present paper and for helpful discussions.

2. General methods for truncated periodic operators

In this section we following [7] consider the scattering theory for operator P_k combining the Floquet-Bloch theory and scattering theory for $1-$D weighted operators.

2.1. **The monodromy matrix and Bloch quasi-momentum.**

We recall first some well-known facts concerning the spectral problem of Sturm-Liouville operators on the line (see [2]). We consider equation

$$P\psi = -\partial_x a(x)\partial_x \psi(x) = \lambda^2 \psi \tag{8}$$

on $\{\psi \in H^1_{\mathrm{loc}}(\mathbb{R}),\ a\partial_x\psi \in H^1_{\mathrm{loc}}(\mathbb{R})\}$ with a strictly positive $a(x)$ as in the Introduction, formula (1) or periodic as a_0 in (2).

Let $\psi_{1,2}$ be solutions of (8) with initial data

$$\psi_1(\lambda,0) = 1,\ (a\partial_x\psi_1)(\lambda,0) = 0;\ \psi_2(\lambda,0) = 0,\ (a\partial_x\psi_2)(\lambda,0) = 1. \tag{9}$$

We define the transfer matrix (propagator) $M_\lambda(0,x)$ for operator P

$$M_\lambda(0,x) = \begin{pmatrix} \psi_1(\lambda,x) & \lambda\psi_2(\lambda,x) \\ \frac{(a\partial_x\psi_1)(\lambda,x)}{\lambda} & (a\partial_x\psi_2)(\lambda,x) \end{pmatrix}. \tag{10}$$

From (9) it follows that $M_\lambda(0,x)$ is the identity matrix. For any solution ψ of (8) matrix $M_\lambda(0,x)$ maps the Cauchy data of ψ at $x = 0$ into the Cauchy data of ψ at point x :

$$M_\lambda(0,x) : \begin{pmatrix} \psi(0) \\ \frac{(a\partial_x\psi)(\lambda,0)}{\lambda} \end{pmatrix} \mapsto \begin{pmatrix} \psi(x) \\ \frac{(a\partial_x\psi)(\lambda,x)}{\lambda} \end{pmatrix}.$$

As the generalized Wronskian associated with ψ_1, ψ_2

$$W[\psi_1,\psi_2] = \psi_1 a\partial_x\psi_2 - \psi_2 a\partial_x\psi_1$$

is constant, we have

$$\det M_\lambda(0,x) = W[\psi_1,\psi_2](1) = W[\psi_1,\psi_2](0) = 1.$$

Equation (8) with $\mathrm{Im}\,\lambda > 0$ has exactly one solution ψ^+ in $L^2(\mathbb{R}_+)$ normalized by the condition $\psi^+(\lambda,0) = 1$, and it has exactly one solution $\psi^- \in L^2(\mathbb{R}_-)$ normalized by the same condition.

Here $\mathbb{R}_\pm$ are semiaxes $x \gtrless 0$. Any solution of (8) can be represented as linear combinations of ψ_1 and ψ_2 and from the normalization of $\psi^\pm$ it follows, that there exist functions $m^\pm = m^\pm(\lambda)$ such that

$$\psi^\pm = \psi_1 + m^\pm(\lambda)\psi_2, \ \operatorname{Im}\lambda > 0.$$

Functions $m^\pm = m^\pm(\lambda)$ are called Weyl's functions and we have

$$\psi_1 + m^+(\lambda)\psi_2 \in L^2(\mathbb{R}_+), \ \psi_1 + m^-(\lambda)\psi_2 \in L^2(\mathbb{R}_-), \ \operatorname{Im}\lambda > 0.$$

Let $a(x)$ be periodic: $a(x+l) = a(x)$. Consider propagator through one period (monodromy matrix):

$$M_\lambda = M_\lambda(0,l) = \begin{pmatrix} \alpha & \beta \\ \gamma & \delta \end{pmatrix}(\lambda) = \begin{pmatrix} \psi_1(\lambda,l) & \lambda\psi_2(\lambda,l) \\ \frac{(a\partial_x\psi_1)(\lambda,l)}{\lambda} & (a\partial_x\psi_2)(\lambda,l) \end{pmatrix}.$$

Denote $F(\lambda) = \frac{1}{2}\operatorname{tr} M_\lambda = (\alpha+\delta)/2 = (\psi_1(\lambda,1) + a\partial\psi_2(\lambda,1)$ the Lyapunov function. Both M_λ and $F(\lambda)$ are entire function of λ and $\det M_\lambda = 1$. The eigenvalues $\mu^\pm(\lambda)$ of M_λ are the roots of the characteristic equation

$$\mu^2 - 2\mu F(\lambda) + 1 = 0. \tag{11}$$

If $\operatorname{Im}\lambda > 0$ then one can select roots $\mu^\pm(\lambda)$ of (11) in such a way that $\mu^\pm(\lambda) = e^{\pm il\theta(\lambda)}$, where $\theta(\lambda)$ is analytic and

$$\operatorname{Im}\theta(\lambda) > 0 \text{ when } \operatorname{Im}\lambda > 0, \tag{12}$$

i.e.,

$$|\mu^+(\lambda)| < 1, \ |\mu^-(\lambda)| > 1, \ \operatorname{Im}\lambda > 0. \tag{13}$$

The roots $\mu^\pm(\lambda)$ for real $\lambda \geq 0$ are defined by continuity in the upper half plane:

$$\mu^\pm(\lambda) = \mu^\pm(\lambda + i0), \ \lambda \in [0,\infty).$$

Since the trace of M_λ is equal to the sum of the eigenvalues $e^{\pm il\theta(\lambda)}$,

$$\cos l\theta = F(\lambda) = \frac{1}{2}(\psi_1 + a\psi_2')(\lambda,l) = \frac{1}{2}(\alpha+\delta). \tag{14}$$

The spectrum of P belongs to the positive part of the energy axis $E = \lambda^2$ and has band structure.

For real $\lambda \geq 0$, the inequality $|F(\lambda)| \leq 1$ defines the spectral bands (zones)

$$b_n = [\lambda_{2n-1}, \lambda_{2n}], \ n = 1, 2, \ldots,$$

on the frequency axis $\lambda = \sqrt{E}$. The bands are defined by the condition $|F(\lambda)| \leq 1$ and $F(\lambda) = \pm 1$ at any band edge $\lambda = \lambda_j$.

The function $\theta(\lambda)$ is real valued when λ belongs to a band. The roots $\mu^\pm(\lambda)$ are complex adjoint there, and $|\mu^\pm| = 1$.

The spectrum of P (on $L^2(\mathbb{R})$) on the frequency axis is $\bigcup_{n=1}^\infty b_n$.

The complimentary open set, given by $|F(\lambda)| > 1$, corresponds to spectral gaps, $\bigcup_{n=1}^\infty g_n$. On gaps, the function $i\theta(\lambda)$ is real valued, the roots $\mu^\pm(\lambda)$ are real and (13) holds.

A point λ_j which belongs to the boundary of a band and the boundary of a gap is called a non-degenerate band edge. If it belongs to the boundary of two different bands, it is called a degenerate band edge.

As in [7] we get that if $\lambda = \lambda_0$ is a non-degenerate band edge, then $F'(\lambda) \neq 0$. If $\lambda = \lambda_0$ is a degenerate edge, then $F'(\lambda) = 0$, $F''(\lambda) \neq 0$. Both eigenvalues of the monodromy matrix M_λ at any band edge are equal to 1 or both are equal to -1.

We normalize the eigenvectors $h^{\pm}(\lambda)$ of M_λ by choosing the first coordinate of $h^{\pm}(\lambda)$ to be equal to one:

$$h^{\pm}(\lambda) = \begin{pmatrix} 1 \\ m^{\pm}(\lambda) \end{pmatrix}.$$

The second coordinates of the vectors $h^{\pm}(\lambda)$ coincide with the Weyl's functions defined above. In fact, if $\psi^{\pm}$ are solutions of the equation $P\psi = \lambda^2\psi$ with the initial Cauchy data given by the eigenvector $h^{\pm}$, then

$$\psi^{\pm}(\lambda, x+l) = e^{\pm il\theta(\lambda)}\psi^{\pm}(\lambda, x) \tag{15}$$

and (13) implies that $\psi^{\pm} \in L^2(\mathbb{R}_{\pm})$ when $\operatorname{Im}\lambda > 0$. From here it follows that $\psi^{\pm}$ coincide with Weyl's solution introduced for general Hamiltonians P, and that the second coordinates of the vectors $h^{\pm}(\lambda)$ are Weyl's functions.

Since

$$\begin{pmatrix} \alpha - e^{\pm il\theta(\lambda)} & \beta \\ \gamma & \delta - e^{\pm il\theta(\lambda)} \end{pmatrix} \begin{pmatrix} 1 \\ m^{\pm} \end{pmatrix} = 0,$$

the following two representations are valid for Weyl's functions:

$$m^{\pm}(\lambda) = \frac{e^{\pm il\theta(\lambda)} - \alpha(\lambda)}{\beta(\lambda)} = \frac{\gamma(\lambda)}{e^{\pm il\theta(\lambda)} - \delta(\lambda)}. \tag{16}$$

2.2. **Reflection coefficient for the truncated periodic operator.**

We consider operator P_k with the truncated periodic coefficient a_k :

$$P_k\psi = -\partial_x a_k(x)\partial_x\psi(x),\ a_k(x) = a(x),\ \text{for } x \in [0, kl];\ a_k(x) = \frac{1}{b_1^2},\ \text{for } x \notin [0, kl],$$

which appears when the propagation of waves through a finite slab of a periodic medium is studied. We shall also consider the limiting case $k = \infty$:

$$P_\infty\psi = -\partial_x a_\infty(x)\partial_x\psi(x),$$

which corresponds to the case of such a long slab that it can be considered as half infinite.

We shall denote the reflection and transmission coefficients for the operator P_k (with compactly supported coefficient a_k) by r_k and t_k, respectively:

$$P_k\psi = \lambda^2\psi,\ \psi = e^{i\lambda b_1 x} + r_k e^{-i\lambda b_1 x},\ x < 0;\ \psi = t_k e^{i\lambda b_1 x},\ x > kl.$$

In the case of the operator P_∞, the solution ψ of the scattering problem is defined as the solution of the equation $P_\infty\psi = \lambda^2\psi$, such that

$$\psi = e^{i\lambda b_1 x} + re^{-i\lambda b_1 x},\ x < 0;\ \psi = c\psi^{+}(\lambda, x),\ x > 0, \tag{17}$$

with some $r = r(\lambda)$, $c = c(\lambda)$. We have the following version of Theorem 3 of S. Molchanov, B. Vainberg in [7]:

Theorem 2. 1) *The transfer matrix over k periods $M_\lambda^k = T_\lambda(0, lk)$ has the form*

$$M_\lambda^k = \begin{pmatrix} \alpha_k & \beta_k \\ \gamma_k & \delta_k \end{pmatrix} = \frac{\sin kl\theta(\lambda)}{\sin l\theta(\lambda)} M_\lambda - \frac{\sin(k-1)l\theta(\lambda)}{\sin l\theta(\lambda)} I, \tag{18}$$

where $\theta = \theta(\lambda)$ is the Bloch function. The elements of M_λ^k satisfy the relations

$$\alpha_k - \delta_k = \frac{\sin kl\theta(\lambda)}{\sin l\theta(\lambda)}(\alpha - \delta),\quad \beta_N = \frac{\sin kl\theta(\lambda)}{\sin l\theta(\lambda)}\beta,$$

$$\gamma_k = \frac{\sin kl\theta(\lambda)}{\sin l\theta(\lambda)}\gamma,\quad \alpha_k + \delta_k = 2\cos kl\theta(\lambda). \tag{19}$$

2) *The reflection coefficients have the forms*

$$r_k(\lambda) = -\frac{(\alpha-\delta)+i(b_1\gamma+\frac{\beta}{b_1})}{2\sin l\theta(\lambda)\frac{\cos kl\theta(\lambda)}{\sin kl\theta(\lambda)}+i(b_1\gamma-\frac{\beta}{b_1})}, \tag{20}$$

$$r(\lambda) = \frac{\frac{\beta}{b_1}+b_1\gamma-i(\alpha-\delta)}{2\sin l\theta(\lambda)-(b_1\gamma-\frac{\beta}{b_1})}. \tag{21}$$

3) *The transmission probability have the form*

$$|t_k(\lambda)|^2 = \frac{4}{\frac{\sin^2 lk\theta}{\sin^2 l\theta}\left((\alpha-\delta)^2+(b_1\gamma+\frac{\beta}{b_1})^2\right)+4} = \frac{1}{\frac{\sin^2 lk\theta}{\sin^2 l\theta}\frac{|r_1|^2}{|t_1|^2}+1}. \tag{22}$$

4) *The reflection coefficients $r_k(\lambda)$ and $r(\lambda)$ are analytic in the upper half plane $\mathbb{C}_+ = \{\lambda : \operatorname{Im}\lambda > 0\}$ and continuous in $\overline{\mathbb{C}}_+$. For any $\lambda \in \overline{\mathbb{C}}_+ \setminus \cup_{n=1}^\infty b_n$ we have $r_k(\lambda) \to r(\lambda)$. When $\lambda \in \cup_{n=1}^\infty b_n$, $r_k(\lambda)$ converges to $r(\lambda)$ in the weak sense:*

$$\int_{-\infty}^{\infty} r_k(\lambda)\varphi(\lambda)d\lambda \to \int_{-\infty}^{\infty} r(\lambda)\varphi(\lambda)d\lambda \quad \text{as } k\to\infty.$$

for any test function $\varphi \in D$.

Proof: We reproduce here the proof of [7] for the sake of completeness with only minor changes due to the "weight" in the definitions of P_k and P_∞. Formula (18) follows by induction from relation (11):

$$M_\lambda^2 - 2\cos l\theta(\lambda)M_\lambda + I = 0.$$

The first three relations of (19) are immediate consequences of (18). In order to get the fourth one we note that the eigenvalues of M_λ^k are $\mu^\pm(\lambda) = e^{\pm ikl\theta(\lambda)}$. Thus,

$$\alpha_k + \delta_k = \operatorname{tr} M_\lambda^k = e^{ikl\theta(\lambda)} + e^{-ikl\theta(\lambda)} = 2\cos kl\theta(\lambda). \tag{23}$$

Next we prove (20). The relation between Cauchy data for the left-to-right scattering solution at $x=0$ and $x=kl$ are given by

$$\begin{pmatrix} \alpha_k & \beta_k \\ \gamma_k & \delta_k \end{pmatrix}\begin{pmatrix} 1+r_k \\ \frac{i}{b_1}(1-r_k) \end{pmatrix} = \begin{pmatrix} t_k \\ \frac{it_k}{b_1} \end{pmatrix} \Leftrightarrow \begin{cases} \alpha_k(1+r_k)+\beta_k(\frac{i}{b_1}(1-r_k)) = t_k \\ \gamma_k(1+r_k)+\delta_k(\frac{i}{b_1}(1-r_k)) = \frac{it_k}{b_1} \end{cases}$$

By dividing the second equation by the first one we arrive at

$$\frac{\gamma_k(1+r_k)+\frac{\delta_k i}{b_1}(1-r_k)}{\alpha_k(1+r_k)+\frac{\beta_k i}{b_1}(1-r_k)} = \frac{i}{b_1}.$$

Solving for r_k we obtain

$$r_k = \frac{\delta_k-\alpha_k-i(b_1\gamma_k+\frac{\beta_k}{b_1})}{\delta_k+\alpha_k+i(b_1\gamma_k-\frac{\beta_k}{b_1})}. \tag{24}$$

Using (19) we get

$$r_k = -\frac{\frac{\sin kl\theta}{\sin l\theta}(\alpha-\delta)+i\left(b_1\frac{\sin kl\theta}{\sin l\theta}\gamma+\frac{1}{b_1}\frac{\sin kl\theta}{\sin l\theta}\beta\right)}{2\cos kl\theta+i\left(b_1\frac{\sin kl\theta}{\sin l\theta}\gamma-\frac{1}{b_1}\frac{\sin kl\theta}{\sin l\theta}\beta\right)}.$$

This justifies (20).

In order to get (21) we note that (17) implies that

$$\begin{pmatrix} 1+r \\ \frac{i}{b_1}(1-r) \end{pmatrix} = c \begin{pmatrix} 1 \\ m^+ \end{pmatrix} \Leftrightarrow \frac{1+r}{\frac{i}{b_1}(1-r)} = \frac{1}{m^+}$$

and therefore,

$$r = \frac{\frac{i}{b_1} - m^+}{\frac{i}{b_1} + m^+}.$$

From here and (16) it follows that

$$r = \frac{\frac{i}{b_1} - \frac{e^{il\theta}-\alpha}{\beta}}{\frac{i}{b_1} + \frac{e^{il\theta}-\alpha}{\beta}} = \frac{\alpha + \frac{i}{b_1}\beta - e^{il\theta}}{e^{il\theta} - (\alpha - \frac{i}{b_1}\beta)}.$$

and

$$r = \frac{\frac{i}{b_1} - \frac{\gamma}{e^{il\theta}-\delta}}{\frac{i}{b_1} + \frac{\gamma}{e^{il\theta}-\delta}} = \frac{\frac{i}{b_1}(e^{il\theta}-\delta) - \gamma}{\frac{i}{b_1}(e^{il\theta}-\delta) + \gamma} = \frac{e^{il\theta} - (\delta - ib_1\gamma)}{e^{il\theta} - (\delta + ib_1\gamma)}.$$

Hence,

$$r\left(2e^{il\theta} - (\alpha - \frac{i}{b_1}\beta) - (\delta + ib_1\gamma)\right) = \alpha + \frac{i}{b_1}\beta - (\delta - ib_1\gamma)$$

and

$$\begin{aligned} r &= \frac{(\alpha + \frac{i}{b_1}\beta) - (\delta - ib_1\gamma)}{2e^{il\theta} - (\alpha - \frac{i}{b_1}\beta) - (\delta + ib_1\gamma)} = \frac{(\alpha - \delta) + i(\frac{\beta}{b_1} + b_1\gamma)}{2e^{il\theta} - (\alpha + \delta) + i(\frac{\beta}{b_1} - b_1\gamma)} = \\ &= \frac{(\alpha - \delta) + i(\frac{\beta}{b_1} + b_1\gamma)}{2i\sin l\theta + i(\frac{\beta}{b_1} - b_1\gamma)}, \end{aligned}$$

where the last equality is a consequence of (14) and it implies (21).

We prove the third statement of the theorem. From (24) it follows

$$|r_k|^2 = \frac{(\delta_k - \alpha_k)^2 + (b_1\gamma_k + \frac{\beta_k}{b_1})^2}{(\delta_k + \alpha_k)^2 + (b_1\gamma_k - \frac{\beta_k}{b_1})^2}. \tag{25}$$

Using that $|r_k|^2 + |t_k|^2 = 1$ we get

$$|t_k|^2 = 1 - |r_k|^2 = \frac{4\delta_k\alpha_k - 4\gamma_k\beta_k}{(\delta_k + \alpha_k)^2 + (b_1\gamma_k - \frac{\beta_k}{b_1})^2}. \tag{26}$$

We use $\det M_\lambda^k = \alpha_k\delta_k - \beta_k\gamma_k = 1$ and get

$$|t_k|^2 = \frac{4}{4 + (\delta_k - \alpha_k)^2 + (b_1\gamma_k + \frac{\beta_k}{b_1})^2} = \frac{4}{\frac{\sin^2 lk\theta}{\sin^2 l\theta}\left((\alpha - \delta)^2 + (b_1\gamma + \frac{\beta}{b_1})^2\right) + 4}.$$

From formulas (25) and (26) we get

$$\frac{|r_k|^2}{|t_k|^2} = \frac{1}{4}\left((\delta_k - \alpha_k)^2 + (b_1\gamma_k + \frac{\beta_k}{b_1})^2\right)$$

and hence, putting $k = 1$,

$$|t_k|^2 = \frac{1}{\frac{\sin^2 lk\theta}{\sin^2 l\theta}\frac{|r_1|^2}{|t_1|^2} + 1}.$$

The analyticity of $r_k(\lambda)$ and $r(\lambda)$ in $\mathbb{C}_+$ and their continuity in $\overline{\mathbb{C}}_+$ follow from the explicit formulas (20), (21). For $\lambda \in \mathbb{C}_+ \bigcup \cup_{n=1}^{\infty} g_n$, we have $\operatorname{Im}\theta(\lambda) > 0$ and $\theta(\lambda)$ is pure imaginary on the gaps g_n. Furthermore, if $\operatorname{Im}\theta(\lambda) > 0$, then

$$\frac{\cos k\theta(\lambda)}{\sin k\theta(\lambda)} \to -i \text{ as } k \to \infty$$

and this justifies the convergence of $r_k(\lambda)$ to r when $\lambda \in \mathbb{C}_+ \bigcup \cup_{n=1}^{\infty} g_n$.

The weak convergence for $\lambda \in \cup_{n=1}^{\infty} b_n$ is a consequence the convergence in the complex half plane.

The proof of Theorem 2 is complete. ∎

Note also the following relations:

$$\frac{|r_k|^2}{|t_k|^2} = \frac{\sin^2 lk\theta}{\sin^2 l\theta} \cdot \frac{|r_1|^2}{|t_1|^2},$$

$$|t_k|^2 = \frac{4}{4\cos^2 kl\theta + \left(b_1 \frac{\sin kl\theta}{\sin l\theta}\gamma - \frac{1}{b_1}\frac{\sin kl\theta}{\sin l\theta}\beta\right)^2} = \frac{4\frac{\sin^2 l\theta}{\sin^2 kl\theta}}{4\sin^2 l\theta\frac{\cos^2 kl\theta}{\sin^2 kl\theta} + \left(b_1\gamma - \frac{\beta}{b_1}\right)^2}.$$

The last formula follows from (26) by using (23).

Formula (22) implies that the perfect transmission ($|t_k|^2 = 1$) occurs whenever $|r_1|^2 = 0$ ($|t_1|^2 = 1$) or if

$$\frac{\sin^2 lk\theta}{\sin^2 l\theta} = 0. \tag{27}$$

For $\theta \in [0, \pi/l]$ equation (27) is satisfied when $\theta lk = m\pi$ for $m = 1, 2, \ldots, k-1$.

Therefore, in the general case ($|r_1|^2 \neq 0$), the transmission probability has $k-1$ peaks with $|t_k|^2 = 1$ in each allowed energy band as θ increases by π/l. Since the peaks in the transmission probability (or in general in the cross section) are associated with resonances, we expect to find $k-1$ resonances near each allowed energy band.

On the gaps, the function $i\theta(\lambda)$ is real valued. Then the transmission probability is given by

$$|t_k(\lambda)|^2 = \frac{1}{\frac{\sinh^2 lki\theta}{\sinh^2 li\theta}\frac{|r_1|^2}{|t_1|^2} + 1}. \tag{28}$$

As $\sinh^2 lki\theta \neq 0$ for $\theta \neq 0$, then in the forbidden zone $|t_k(\lambda)|^2 \neq 1$ unless $|t_1|^2 = 1,\ |r_1|^2 = 0$. Hence there are no resonances below the gaps.

On the gaps, the reflection coefficient for the half-periodic system $r(\lambda)$ satisfy

$$|r(\lambda)|^2 = \frac{\left(\frac{\beta}{b_1} + b_1\gamma\right)^2 + (\alpha - \delta)^2}{e^{2i\theta} + e^{-2i\theta} - 2 + \left(b_1\gamma - \frac{\beta}{b_1}\right)^2} = \frac{\left(\frac{\beta}{b_1} + b_1\gamma\right)^2 + (\alpha - \delta)^2}{(\alpha + \delta)^2 - 4 + \left(b_1\gamma - \frac{\beta}{b_1}\right)^2} = 1.$$

In [7], Theorem 5, was shown that

Lemma 1. *If λ_0 is a degenerate band edge, i.e. $F(\lambda_0) = \pm 1$, $F'(\lambda_0) = 0$, then the reflection coefficient r_k is zero, $r_k(\lambda_0) = 0$.*

The proof uses the fact that at any degenerate band edge $\lambda = \lambda_0$ the monodromy matrix $M_{\lambda_0} = \pm I$ and $F''(\lambda_0) \neq 0$. This allows to pass to the limit in (20) as $\lambda \to \lambda_0$. The numerator in the right hand side of (20) vanishes as $\lambda \to \lambda_0$. The denominator converges to $\pm 2/k$, since $\theta(\lambda_0) = n\pi$.

Thus the medium is transparent for the plane wave with the frequency λ_0 and we expect to find a resonance $\lambda \in \mathbb{C}_-$ below the degenerated band edge λ_0.

3. The monodromy matrix for P_k

In this section we give expressions for the elements of the monodromy matrix M_λ.

Let $a(x)$ be 1−periodic function equal to a_0 for $x \in [0,1)$ as in (1), (2):

$$a_0(x) = \begin{cases} b_2^{-2} & \text{for } x \in [0, x_2) \\ b_1^{-2} & \text{for } x \in [x_2, 1) \end{cases}$$

and

$$a(x) = \begin{cases} a_0(x-j) & \text{for } x \in [j, j+1),\ 0 \le j \le k-1 \\ b_1^{-2} & \text{elsewhere} \end{cases}$$

for $k \geq 2$, where k is the number of identical cells. The period $l = 1$. The normalized solutions $\psi_1(\lambda,x)$, $\psi_2(\lambda,x)$,

$$-\partial_x a(x)\partial_x \psi_i = \lambda^2 \psi_i,\ \psi_1(\lambda,0) = (b_2^{-2}\partial_x\psi_2)(\lambda,0) = 1,\ \psi_2(\lambda,0) = (b_2^{-2}\partial_x\psi_1)(\lambda,0) = 0,$$

satisfy (see [4])

$$\psi_1(\lambda,x) = \begin{cases} \frac{1}{2}e^{i\lambda b_2 x} + \frac{1}{2}e^{-i\lambda b_2 x} & \text{for } x \in [0, x_2) \\ Ae^{i\lambda b_1 x} + Be^{-i\lambda b_1 x} & \text{for } x \in [x_2, 1) \end{cases}$$

$$\psi_2(\lambda,x) = \begin{cases} -\frac{ib_2}{2\lambda}e^{i\lambda b_2 x} + \frac{ib_2}{2\lambda}e^{-i\lambda b_2 x} & \text{for } x \in [0, x_2) \\ Ce^{i\lambda b_1 x} + De^{-i\lambda b_1 x} & \text{for } x \in [x_2, 1) \end{cases}$$

with A, B, C, D chosen such that ψ_j and $a(x)\partial_x\psi_j$ are continuous at x_2 :

$$\begin{aligned}
A &= \frac{1}{4b_2}\left[(b_2+b_1)e^{i\lambda x_2(b_2-b_1)} + (b_2-b_1)e^{-i\lambda x_2(b_2+b_1)}\right], \\
B &= \frac{1}{4b_2}\left[(b_2+b_1)e^{-i\lambda x_2(b_2-b_1)} + (b_2-b_1)e^{i\lambda x_2(b_2+b_1)}\right], \\
C &= \frac{i}{4\lambda}\left[-(b_2+b_1)e^{i\lambda x_2(b_2-b_1)} + (b_2-b_1)e^{-i\lambda x_2(b_2+b_1)}\right], \\
D &= \frac{i}{4\lambda}\left[(b_2+b_1)e^{-i\lambda x_2(b_2-b_1)} - (b_2-b_1)e^{i\lambda x_2(b_2+b_1)}\right].
\end{aligned}$$

We get the monodromy matrix

$$M_\lambda = \begin{pmatrix} \alpha & \beta \\ \gamma & \delta \end{pmatrix} = \begin{pmatrix} \psi_1(\lambda,1) & \lambda\psi_2(\lambda,1) \\ \frac{1}{\lambda}(\frac{1}{b_1^2}\partial_x\psi_1)(\lambda,1) & (\frac{1}{b_1^2}\partial_x\psi_2)(\lambda,1) \end{pmatrix}$$

with

$$\begin{aligned}
\alpha &= \psi_1(\lambda,1) = \frac{b_2+b_1}{2b_2}\cos\lambda[b_1(1-x_2)+x_2b_2] + \frac{b_2-b_1}{2b_2}\cos\lambda[b_1(1-x_2)-x_2b_2], \\
\beta &= \lambda\psi_2(\lambda,1) = \frac{b_2+b_1}{2}\sin\lambda[b_1(1-x_2)+x_2b_2] - \frac{b_2-b_1}{2}\sin\lambda[b_1(1-x_2)-x_2b_2], \\
\gamma &= \frac{1}{\lambda}(\frac{1}{b_1^2}\partial_x\psi_1)(\lambda,1) = -\frac{b_2+b_1}{2b_1b_2}\sin\lambda[b_1(1-x_2)+x_2b_2] - \frac{b_2-b_1}{2b_1b_2}\sin\lambda[b_1(1-x_2)-x_2b_2], \\
\delta &= (\frac{1}{b_1^2}\partial_x\psi_2)(\lambda,1) = \frac{b_2+b_1}{2b_1}\cos\lambda[b_1(1-x_2)+x_2b_2] - \frac{b_2-b_1}{2b_1}\cos\lambda[b_1(1-x_2)-x_2b_2].
\end{aligned}$$

Then

$$\operatorname{tr}(M_\lambda) = \alpha + \delta = (\rho + 1)\cos\lambda[b_1(1 - x_2) + x_2 b_2] - (\rho - 1)\cos\lambda[b_1(1 - x_2) - x_2 b_2],$$

where $\rho = \frac{b_2^2+b_1^2}{2b_2 b_1}$. The Bloch quasi-momentum $\theta = \theta(\lambda)$ satisfy

$$2\cos\theta = \operatorname{tr} M_\lambda.$$

The first formula in (22) implies that the one cell medium is perfectly transparent: $|t_1(\lambda_0)|^2 = 1$, $|r_1(\lambda_0)|^2 = 0$, if $\alpha - \delta = 0$, $b_1\gamma + \frac{\beta}{b_1} = 0$. We get $\lambda = \lambda_0 = \pi m / x_2 b_2$.

Note that there is a resonance $\lambda \in \operatorname{Res}(P_1)$ for the one cell operator such that $\operatorname{Re}\lambda = \lambda_0$ (see equation (35) with $b_3 = b_1$ and $x_1 = 0$).

If $\lambda_0 = \frac{\pi m}{x_2 b_2}$ then we have

$$2F(\lambda_0) = 2\cos\theta(\lambda_0) = \pm 2\cos\left(\frac{(1 - x_2)b_1}{x_2 b_2}\pi m\right), \text{ if } m \text{ is even (odd)}.$$

Thus in general situation, $\frac{(1-x_2)b_1}{x_2 b_2} \notin \mathbb{Q}$, non-rational, λ_0 is an interior point of a spectral band.

If $x_2 b_2 = (1 - x_2)b_1$ then the Lyapunov function satisfies

$$2F(\lambda) = (\rho + 1)\cos(2\lambda b_2 x_2) - (\rho - 1) \tag{29}$$

and we have $F(\lambda_0) = 1$, $F'(\lambda_0) = 0$ and $F''(\lambda_0) \neq 0$. Hence λ_0 is degenerate band edge.

The non-degenerate band edge is then given by the equation

$$(\rho + 1)\cos(2\lambda b_2 x_2) - (\rho - 1) = -2 \;\Leftrightarrow\; \lambda = \frac{1}{2b_2 x_2}\left(\pm\arccos\left(\frac{\rho - 3}{\rho + 1}\right) + 2\pi n\right).$$

4. Explicit construction of the resolvent and resonances

In this section we define the resonances as the poles of the analytic continuation of the resolvent $R(\lambda)$ to $\mathbb{C}_-$.

4.1. Representation of the resolvent.

In this section we revue some formulas used by Valeria Banica in [4], where she considered the local and global dispersion and the Stricharts inequalities for certain one-dimensional Schrödinger and wave equations with step-like coefficients. The systems are described by the one-dimensional Schrödinger equation

$$\begin{cases} (i\partial_t + \partial_x a(x)\partial_x)u(t,x) &= 0 \text{ for } (t,x) \in (0,\infty) \times \mathbb{R}, \\ u(0,x) &= u_0(x) \in L^2(\mathbb{R}) \end{cases} \tag{30}$$

or by the one-dimensional wave equation

$$\begin{cases} (\partial_t^2 - \partial_x a(x)\partial_x)v(t,x) &= 0 \text{ for } (t,x) \in \mathbb{R} \times \mathbb{R}, \\ v(0,x) &= u_0(x) \in L^2(\mathbb{R}), \\ \partial_t v(0,x) &= 0 \end{cases} \tag{31}$$

for a positive step-like function $a(x)$ with a finite number of discontinuities.

Consider a partition of the real axis

$$-\infty = x_0 < x_1 < x_2 < \ldots < x_{n-1} < x_n = \infty$$

and a step function

$$a(x) = b_i^{-2} \text{ for } x \in (x_{i-1}, x_i),$$

where b_i are positive numbers.

The operator $P := -\partial_x a(x)\partial_x$ defined from $\{u \in H^1(\mathbb{R}),\ a\partial_x u \in H^1(\mathbb{R})\}$ to $L^2(\mathbb{R})$ is self-adjoint. For $\operatorname{Im}\lambda > 0$, we define $R(\lambda)v = (-\partial_x a(x)\partial_x - \lambda^2)^{-1}v$ the resolvent of P.

Our choice of the spectral parameter λ is related to ω in [4] by $\lambda = i\omega$. We use the expression for the resolvent obtained in [4].

On each interval (x_i, x_{i+1}) $R(\lambda)v$ is a finite sum of terms

$$R(\lambda)v(x) = -\sum_{\text{finite}} Ce^{i\lambda\beta(x)} \int_{I(x_i)} \frac{v(y)}{2i\lambda} \frac{e^{\pm i\lambda b_i y}}{\det D_n(-i\lambda)} dy - \int_{-\infty}^{\infty} \frac{v(y)}{2i\lambda} b_i e^{i\lambda b_i |x-y|} dy, \tag{32}$$

where $I(x_i)$ is either $(-\infty, x_i)$ or (x_i, ∞) and

$$\det D_2(-i\lambda) = (b_1 + b_2)e^{i\lambda x_1(b_2-b_1)}.$$

In [4] Banica defines all $\det D_n$ by induction. Let

$$\det \widetilde{D_2(-i\lambda)} = (b_2 - b_1)e^{-i\lambda x_1(b_1+b_2)}.$$

We have the following induction relations for $n \geq 3$

(33)

$$\det D_n = e^{i\lambda b_n x_{n-1}} \left[(b_{n-1} - b_n)e^{i\lambda b_{n-1}x_{n-1}} \det \widetilde{D_{n-1}} - (b_{n-1} + b_n)e^{-i\lambda b_{n-1}x_{n-1}} \det D_{n-1}\right]$$

$$\det \widetilde{D_n} = e^{-i\lambda b_n x_{n-1}} \left[(b_{n-1} - b_n)e^{-i\lambda b_{n-1}x_{n-1}} \det D_{n-1} - (b_{n-1} + b_n)e^{i\lambda b_{n-1}x_{n-1}} \det \widetilde{D_{n-1}}\right].$$

We define for $n \geq m \geq 2$

$$Q_m(-i\lambda) = e^{2i\lambda b_m x_m} \frac{\det \widetilde{D_m}}{\det D_m},\ d_{m-1} = \frac{b_{m-1} - b_m}{b_{m-1} + b_m}.$$

Then we have for $n \geq 3$

$$\det D_n(i\lambda) = (b_1 + b_2)e^{i\lambda(b_2-b_1)x_1} \Pi_{j=2\dots n-1}(b_j + b_{j+1})e^{-i\lambda(b_j - b_{j+1})x_j}(1 - d_j Q_j(-i\lambda)).$$

We have induction formula on the Q_m's

$$Q_m(-i\lambda) = e^{2i\lambda b_m(x_m - x_{m-1})} \frac{-d_{m-1} + Q_{m-1}(-i\lambda)}{1 - d_{m-1}Q_{m-1}(-i\lambda)}. \tag{34}$$

Note that a linear-fractional transform on the unit disc occurs in (34) for $\operatorname{Im}\lambda \geq 0$.

If $\operatorname{Im}\lambda \leq 0$ then $|e^{2i\lambda b_m(x_m - x_{m-1})}| \geq 1$. We use that $|d_n| < 1$ and for any n we can find $\epsilon_n > 0$ such that for every complex λ with

$$\operatorname{Im}\lambda \geq -\epsilon_n$$

the estimate

$$|Q_2(-i\lambda)| = |d_1 e^{2i\lambda b_2(x_2 - x_1)}| < 1$$

holds and gives by induction

$$|Q_m(-i\lambda)| < 1,\ n \geq m \geq 2.$$

Hence $(\det D_n(-i\lambda))^{-1}$ is uniformly bounded and well defined in this region, which contains the real axis. Therefore $i\lambda R(\lambda)u_0(x)$ can be analytically continued. The spectral theorem gives

Lemma 2. *The solution of the Schrödinger equation (30) verifies*

$$u(t,x) = \int_{-\infty}^{\infty} e^{it\lambda^2} \lambda R(\lambda)u_0(x) \frac{d\lambda}{\pi}.$$

The solution of the wave equation (31) verifies

$$v(t,x) = \int_{-\infty}^{\infty} e^{it\lambda} i\lambda R(\lambda)u_0(x) \frac{d\lambda}{2\pi}.$$

Due to formula (32), the resonance spectrum $\mathrm{Res}\,(P)$ consist of zeros of $\det D_n(-i\lambda)$ or equivalently the zeros of $1-d_{n-1}Q_{n-1}(-i\lambda)$ as by (33), equation $\det D_n(-i\lambda)=0$ is equivalent to

$$Q_{n-1}(-i\lambda)=\frac{1}{d_{n-1}}.$$

By considerations before Lemma 2, for each $n\geq 2$ there is $\epsilon_n>0$ such that all resonances verify $\mathrm{Im}\,\lambda<-\epsilon_n$. For $n=2$ there are no zeros.

For $n=3$ the resonances are solutions of the equation $\det D_3(-i\lambda)=0$, $\lambda=\lambda_1+i\lambda_2,\ \lambda_j\in\mathbb{R}$, with constant imaginary part:

$$\lambda_1=\frac{\pi m}{2b_2(x_2-x_1)},\ \lambda_2=-\frac{1}{2b_2(x_1-x_2)}\ln\left|\frac{(b_2-b_3)(b_2-b_1)}{(b_2+b_3)(b_1+b_2)}\right|<0, \tag{35}$$

where $m=0,\pm2,\pm4\ldots$, is even, if $(b_2-b_3)(b_2-b_1)>0$ or $m=\pm1,\pm3,\pm5\ldots$, is odd, if $(b_2-b_3)(b_2-b_1)<0$.

For $n>3$ the resonance spectrum can be obtained numerically using the induction relations (33).

4.2. **Locally periodic media.** Suppose that the profile of $a(x)$ consist of a finite number identical elements, obtained by juxtaposing of k unit cells. Outside the interval $[0,k)$ the coefficient is constant. We make the following choice: suppose $n=2k+1$ odd, $b_1=b_3=b_5=\ldots=b_n$, $b_2=b_4=\ldots=b_{n-1}$, and put

$$x_1=0,\ 0<x_2<1,\ x_3=1,\ d=\frac{b_2-b_1}{b_2+b_1},\ \lambda=\lambda_1+i\lambda_2,\ \lambda_1\in\mathbb{R},\ \lambda_2<0.$$

We have $x_{2k+1}=k,\ x_{2k}=k-1+x_2$. Let

$$a_0(x)=\begin{cases} b_2^{-2} & \text{for } x\in[0,x_2)\\ b_1^{-2} & \text{for } x\in[x_2,1)\end{cases} \tag{36}$$

and

$$a(x)=\begin{cases} a_0(x-j) & \text{for } x\in[j,j+1),\ 0\leq j\leq k-1\\ b_1^{-2} & \text{elsewhere}\end{cases} \tag{37}$$

for $k\geq 2$. Here k is the number of identical cells.

The function $a(x)$ is called *locally periodic* or *finite periodic* on the interval $[0,k)$ with k cells.

Then, with $n=2k+1$,

$$\det D_n(-i\lambda)=(b_1+b_2)^{n-1}e^{-i\lambda(b_2-b_1)kx_2}\Pi_{i=2,\ldots,n-1}\left(1-(-1)^i dQ_i(-i\lambda)\right),$$

where

$$Q_{2k}(-i\lambda)=e^{2i\lambda b_2(k-1+x_2))}\frac{\det\tilde{D}_{2k}}{\det D_{2k}},\ Q_{2k+1}(-i\lambda)=e^{2i\lambda b_1 k}\frac{\det\tilde{D}_{2k+1}}{\det D_{2k+1}} \tag{38}$$

For $k=1,2,3,\ldots$ the resonances are the solutions of the equation

$$\det D_{2k+1}(-i\lambda)=0 \tag{39}$$

or equivalently

$$Q_{2k}(-i\lambda)=\frac{1}{d}, \tag{40}$$

where

$$
\begin{aligned}
&Q_{2k}=e^{2i\lambda b_2x_2}\frac{d+Q_{2k-1}}{1+dQ_{2k-1}},\quad Q_{2k-1}=e^{2i\lambda b_1(1-x_2)}\frac{-d+Q_{2k-2}}{1-dQ_{2k-2}}\\
&Q_2=e^{2i\lambda b_2x_2}d.
\end{aligned}
\tag{41}
$$

Note that if condition (6) is satisfied: $b_2x_2=b_1(1-x_2)$, then $Q_m(-i\lambda)$ as function of $\operatorname{Re}\lambda$ is periodic with the period π/b_2x_2, which implies the same property for any solutions of equation (40). The resonance spectrum is then periodic as stated in the Introduction, Theorem 1.

5. The poles of analytic continuation of the reflection coefficient r_k to $\mathbb{C}_-$

Let r_k be reflection coefficient (24). In this section we express r_k using the iteration formulas in section 4 and extend $r_k(\lambda)$ to $\lambda\in\mathbb{C}_-$. We show explicitly that the resonances defined in (39) or (40) are the poles of r_k,

$$\frac{1}{r_k}=0\ \Leftrightarrow\ \det D_{2k+1}(-i\lambda)=0\ \Leftrightarrow\ Q_{2k}(-i\lambda)=\frac{1}{d},$$

We consider the equation $P_1u=-\partial_xa(x)\partial_xu=\lambda^2u$ corresponding to the system with one unit-cell, $a(x)=a_0(x)$, for $x\in[0,1)$ and $a=1/b_1^2$ outside $[0,1)$. Taking solution

$$u(x)=A_0e^{i\lambda b_1x}+A_0'e^{-i\lambda b_1x},\ x<0\text{ and }u(x)=\tilde{A}_0e^{i\lambda b_1x}+\tilde{A}_0'e^{-i\lambda b_1x},\ x>1,\tag{42}$$

the matching conditions imply

$$\begin{pmatrix}\tilde{A}_0\\ \tilde{A}_0'\end{pmatrix}=T\begin{pmatrix}A_0\\ A_0'\end{pmatrix},\tag{43}$$

where T is called transmission matrix (see [1]).

Then coefficients of the solution of the problem with $k-$unit cells $P_ku=-\partial_xa(x)\partial_xu=\lambda^2u$ can be calculated by iteration. Taking solution

$$u(x)=A_{-1}e^{i\lambda b_1x}+A_{-1}'e^{-i\lambda b_1x},\ x<0\text{ and }u(x)=\tilde{A}_ke^{i\lambda b_1x}+\tilde{A}_k'e^{-i\lambda b_1x},\ x>k,\tag{44}$$

the coefficients of the two external regions $x<0$ and $x>k$ are related by

$$\begin{pmatrix}A_k\\ A_k'\end{pmatrix}=\tilde{T}(\lambda)\begin{pmatrix}A_{-1}\\ A_{-1}'\end{pmatrix},\tag{45}$$

where

$$\tilde{T}(\lambda)=\begin{pmatrix}e^{-il(k+1)\lambda b_1}&0\\0&e^{il(k+1)\lambda b_1}\end{pmatrix}Q^k\begin{pmatrix}e^{il\lambda b_1}&0\\0&e^{-il\lambda b_1}\end{pmatrix}=,\tag{46}$$

where

$$Q=\begin{pmatrix}Q_{11}(\lambda)&Q_{12}(\lambda)\\Q_{21}(\lambda)&Q_{22}(\lambda)\end{pmatrix},\ \det Q=1,\ Q_{12}(\lambda)=Q_{21}(-\lambda),\ Q_{11}(-\lambda)=Q_{22}(\lambda)$$

is called iteration matrix

$$Q(\lambda)=D(\lambda)T(\lambda),\ D=\begin{pmatrix}e^{i\lambda b_1}&0\\0&e^{-i\lambda b_1}\end{pmatrix}.\tag{47}$$

Next we relate the iteration matrix Q and the monodromy matrix M_λ.

Relation between the Cauchy data and coefficients in (44) is given by

$$\begin{pmatrix}u(0)\\ \frac{(a\partial_xu)(\lambda,0)}{\lambda}\end{pmatrix}=\begin{pmatrix}1&1\\ \frac{i}{b_1}&-\frac{i}{b_1}\end{pmatrix}\begin{pmatrix}A_0\\ A_0'\end{pmatrix}=L\begin{pmatrix}A_0\\ A_0'\end{pmatrix}$$

and

$$\begin{pmatrix} u(1) \\ \frac{(a\partial_x u)(\lambda,1)}{\lambda} \end{pmatrix} = \begin{pmatrix} 1 & 1 \\ \frac{i}{b_1} & -\frac{i}{b_1} \end{pmatrix} \begin{pmatrix} e^{i\lambda b_1} & 0 \\ 0 & e^{-i\lambda b_1} \end{pmatrix} \begin{pmatrix} \tilde{A}_0 \\ \tilde{A}_0' \end{pmatrix} = LD \begin{pmatrix} \tilde{A}_0 \\ \tilde{A}_0' \end{pmatrix}.$$

Using

$$M_\lambda \begin{pmatrix} u(0) \\ \frac{(a\partial_x u)(\lambda,0)}{\lambda} \end{pmatrix} = \begin{pmatrix} u(1) \\ \frac{(a\partial_x u)(\lambda,1)}{\lambda} \end{pmatrix}$$

and definition of T, equation (43), we get

$$M_\lambda = LDTL^{-1} = LQL^{-1}, \text{ with } L = \begin{pmatrix} 1 & 1 \\ \frac{i}{b_1} & -\frac{i}{b_1} \end{pmatrix}. \tag{48}$$

We have

$$\begin{aligned} Q_{12}(\lambda) &= e^{i\lambda(1-x_2)b_1} \frac{b_2^2 - b_1^2}{4b_1b_2} \left(e^{-i\lambda b_2 x_2} - e^{i\lambda b_2 x_2}\right), \\ Q_{22}(\lambda) &= e^{-i\lambda b_1(1-x_2)} \left((r+1)e^{-i\lambda b_2 x_2} - (r-1)e^{i\lambda b_2 x_2}\right). \end{aligned}$$

As

$$\begin{aligned} \det \tilde{D}_3 &= e^{-i\lambda b_1 x_2}(b_2^2 - b_1^2)(e^{-i\lambda b_2 x_2} - e^{i\lambda b_2 x_2}), \\ \det D_3 &= e^{i\lambda b_1 x_2} \left((b_2 - b_1)^2 e^{i\lambda b_2 x_2} - (b_2 + b_1)^2 e^{-i\lambda b_2 x_2}\right), \end{aligned}$$

then

$$Q_{12}(\lambda) = \frac{e^{i\lambda b_1}}{4b_1b_2} \det \tilde{D}_3, \; Q_{22}(\lambda) = -\frac{e^{-i\lambda b_1}}{4b_1b_2} \det D_3. \tag{49}$$

Using the iteration relations between $\det \tilde{D}_{2k-1}, \; \det D_{2k-1}$ and $\det \tilde{D}_{2k+1}, \; \det D_{2k+1}$ we get

Lemma 3. *We have*

$$Q^k = \begin{pmatrix} Q_{22}^{(k)}(-\lambda) & Q_{12}^{(k)}(\lambda) \\ Q_{12}^{(k)}(-\lambda) & Q_{22}^{(k)}(\lambda) \end{pmatrix},$$

where

$$Q_{12}^{(k)} = \frac{e^{ki\lambda b_1}}{(4b_1b_2)^k} \det \tilde{D}_{2k+1}, \; Q_{22}^{(k)} = -\frac{e^{-ik\lambda b_1}}{(4b_1b_2)^k} \det D_{2k+1}.$$

Using (48) we have also

$$Q^k = L^{-1} M_\lambda^k L = \begin{pmatrix} \frac{1}{2}(\alpha_k + \beta_k \frac{i}{b_1}) - \frac{ib_1}{2}(\gamma_k + \delta_k \frac{i}{b_1}) & \frac{1}{2}(\alpha_k - \beta_k \frac{i}{b_1}) - \frac{ib_1}{2}(\gamma_k - \delta_k \frac{i}{b_1}) \\ \\ \frac{1}{2}(\alpha_k + \beta_k \frac{i}{b_1}) + \frac{ib_1}{2}(\gamma_k + \delta_k \frac{i}{b_1}) & \frac{1}{2}(\alpha_k - \beta_k \frac{i}{b_1}) + \frac{ib_1}{2}(\gamma_k - \delta_k \frac{i}{b_1}) \end{pmatrix}.$$

Using equation (24) we get

$$r_k = -\frac{(\alpha_k - \delta_k) + i(b_1\gamma_k + \frac{\beta_k}{b_1})}{\alpha_k + \delta_k + i(b_1\gamma_k - \frac{\beta_k}{b_1})} = -\frac{2Q_{21}^{(k)}(\lambda)}{2Q_{22}^{(k)}(\lambda)} = -\frac{Q_{21}^{(k)}(\lambda)}{Q_{22}^{(k)}(\lambda)}.$$

Let first $k = 1$. Using equation (49) we get

$$Q_{21}(\lambda) = -e^{-i2\lambda(1-x_2)b_1} Q_{12} = -\frac{e^{-i\lambda(1-x_2)b_1} e^{i\lambda b_1 x_2}}{4b_1b_2} \det \tilde{D}_3(\lambda)$$

Hence

$$r_1 = -\frac{e^{-2i\lambda b_1(1-x_2)}e^{i\lambda b_1(1-x_2)}e^{i\lambda b_1 x_2}\det \tilde{D}_3}{e^{-i\lambda b_1}\det D_3} =$$

$$= -e^{-2i\lambda b_1(1-x_2)}e^{2i\lambda b_1 x_2}\frac{\det \tilde{D}_3}{\det D_3} = -e^{-2i\lambda b_1(1-x_2)}Q_3(-i\lambda).$$

For $k > 1$ we use

$$Q^k = \frac{\sin k\theta l}{\sin \theta l}Q - \frac{\sin(k-1)\theta l}{\sin \theta l}I = \begin{pmatrix} \frac{\sin k\theta l}{\sin\theta l}Q_{11} - \frac{\sin(k-1)\theta l}{\sin\theta l} & \frac{\sin k\theta l}{\sin\theta l}Q_{12} \\ \frac{\sin k\theta l}{\sin\theta l}Q_{21} & \frac{\sin k\theta l}{\sin\theta l}Q_{22} - \frac{\sin(k-1)\theta l}{\sin\theta l} \end{pmatrix}$$

and get

$$Q^{(k)}_{21} = -e^{-i2\lambda(1-x_2)b_1}Q^{(k)}_{12} = -e^{-i2\lambda(1-x_2)b_1}\frac{e^{ki\lambda b_1}}{(4b_1b_2)^k}\det \tilde{D}_{2k+1}.$$

Hence, by (24),

$$r_k = -\frac{Q^{(k)}_{21}}{Q^{(k)}_{22}} = -\frac{e^{-i2\lambda(1-x_2)b_1}e^{ki\lambda b_1}\det \tilde{D}_{2k+1}}{e^{-ik\lambda b_1}\det D_{2k+1}} = -e^{-i2\lambda(1-x_x)b_1}e^{2ki\lambda b_1}\frac{\det \tilde{D}_{2k+1}}{\det D_{2k+1}}.$$

We have

$$r_k = -e^{-2i\lambda b_1(1-x_2)}Q_{2k+1}(-i\lambda) = -\frac{-d + Q_{2k}(-i\lambda)}{1 - dQ_{2k}(-i\lambda)}. \tag{50}$$

Thus we have proved that the poles of r_k on $\mathbb{C}_-$ coincide with the solutions of (40):

$$1 - dQ_{2k}(-i\lambda) = 0 \ \Leftrightarrow\ Q_{2k}(-i\lambda) = \frac{1}{d}.$$

Hence, we have

Proposition 1. *The reflection coefficient* $r_k(\lambda)$ *continuous to* $\mathbb{C}_-$ *with the poles at the resonance spectrum* $\mathrm{Res}\,(P_k)$.

6. CONVERGENCE OF THE RESONANCES TO THE REAL AXIS AS $k \to \infty$

In this section we prove that the resonances spectrum $\mathrm{Res}(P_k)$ converges to the real axes as $k \to \infty$.

First we note that the function $\theta(\lambda) = \arccos\left((\alpha(\lambda) + \delta(\lambda))/2\right)$ has analytic continuation onto the domain $\mathbb{C} \setminus \bigcup_{n=1}^{\infty} g_n$ by the formula $\theta(\overline{\lambda}) = \overline{\theta(\lambda)}$ and $\mathrm{Im}\,\theta(\lambda) < 0$ for $\mathrm{Im}\,\lambda < 0$. For $\lambda \in \bigcup_{n=1}^{\infty} g_n$ we set $\theta(\lambda) = \theta(\lambda - i0)$ and θ is pure imaginary there.

By Proposition 1 the function $r_k(\lambda)$ is analytic in $\lambda \in \mathbb{C}_- \setminus \mathrm{Res}\,(P_k)$, and the formula

$$r_k(\lambda) = -\frac{(\alpha - \delta) + i(b_1\gamma + \frac{\beta}{b_1})}{2\sin l\theta(\lambda)\frac{\cos kl\theta(\lambda)}{\sin kl\theta(\lambda)} + i(b_1\gamma - \frac{\beta}{b_1})}$$

extends to $\mathbb{C}_- \setminus \mathrm{Res}\,(P_k)$, where we have $\mathrm{Im}\,\theta(\lambda) < 0$.

Furthermore, if $\mathrm{Im}\,\theta(\lambda) < 0$, then

$$\frac{\cos k\theta(\lambda)}{\sin k\theta(\lambda)} \to i \text{ as } k \to \infty,$$

and we have

$$r_k \to \frac{i(\alpha - \delta) - (b_1\gamma + \frac{\beta}{b_1})}{2\sin l\theta(\lambda) + (b_1\gamma - \frac{\beta}{b_1})} = \tilde{r}(\lambda).$$

Note that for $\lambda \in \mathbb{R}$, $\tilde{r}(\lambda) = \overline{r(-\lambda)}$.

The limit extends also to $\lambda \in \cup_{n=1}^{\infty} g_n$, where $\theta(\lambda)$ is pure imaginary.

Let $g_k(\lambda)$, $g(\lambda)$ denote the denominators of r_k respectively $\tilde{r}$ for $\lambda \in \mathbb{C}_-$. Then

$$g_k(\lambda) \ \to \ g(\lambda) = 2 \sin l\theta(\lambda) + \left(b_1\gamma - \frac{\beta}{b_1} \right)$$

uniformly on any compact subsets of $\mathbb{C}_-$ and the limiting function g is analytic on $\mathbb{C}_-$.

For any k all zeros of g_k have negative imaginary part: $\operatorname{Res}(P_k) \in \mathbb{C}_-$. Then, by the Hurwitz's theorem, the zeros of g_k can only converge to the real axis. ∎

7. The limit $\lim_{k\to\infty} r_k$ as a fixed point of a sequence of linear-fractional automorphisms of the unit disk

Equation (50) together with iteration relations (50) shows that for $\lambda \in \mathbb{R}$ real and for all $k = 1, 2, 3, \ldots$ the reflection coefficients for the $k+1$ and k cells media are related by $r_{k+1} = f_\lambda(r_k)$, where f_λ is linear-fraction automorphism of the unit disk. Hence we get

$$r_k = f_\lambda^{[k]}(r_1) := \underbrace{f_\lambda \circ f_\lambda \ldots f_\lambda}_{k \text{ iterates}}(r_1). \tag{51}$$

Here r_1 is the reflection coefficient for P_1,

$$r_1 = -\frac{(1 - e^{2i\lambda b_2 x_2})d}{1 - d^2 e^{2i\lambda b_2 x_2}}$$

and for $\lambda \in \mathbb{R}$ we have

$$|r_1|^2 \le \frac{4d^2}{1 + 4d^2 + d^4} < 1.$$

In this section we will consider the limit of the sequence $f_\lambda^{[k]}$ as $k \to \infty$.

First we recall some well-known facts on the convergence behavior of a sequence $\{f^{[k]}\}$ when f is general linear-fractional automorphism f of the unit disc $D = \{z \in \mathbb{C};\ |z| < 1\}$,

$$f(z) = \frac{b - z}{1 - \bar{b}z},\ b \in D,\ z \in \mathbb{C} \setminus \{1/\bar{b}\}.$$

We refer to the paper of Burckel [5]) for the details.

In general situation ($b \neq 0$), f has two fixed points z_1, z_2. There are three cases to consider.

Hyperbolic: f has two (distinct) fixed points on ∂D

$$|z_1| = |z_2| = 1,\ z_1 \neq z_2.$$

In this case the sequence $\{f^{[k]}\}$ converges uniformly on compact subsets in D to one of these points.

Parabolic: f has one (double) fixed point on ∂D

$$z_1 = z_2,\ \text{with } |z_1| = 1.$$

In this case the sequence $\{f^{[k]}\}$ converges uniformly on compact subsets in D to this fixed point.

Elliptic: f has two fixed points: one fixed point $z_1 \in D$ and one fixed point $z_2 = 1/\bar{z} \notin D$. In this case either f is periodic in the sense that $f^{[n]} = I$ for some n, or the orbit $\{f^{[k]};\ n \in \mathbb{N}\}$ is dense in the compact group of all conformal automorphisms of D which fix z_1.

We apply these results to $f = f_\lambda$. In order to simplify the formulas we suppose

$$b_2 x_2 = b_1(1 - x_2). \tag{52}$$

Then we have the following expression for f_λ :

$$f_\lambda(z) = \frac{-d + \eta \frac{d+\eta z}{1+d\eta z}}{1 - d\eta \frac{d+\eta z}{1+d\eta z}}, \text{ where } \eta := e^{2i\lambda b_2 x_2}.$$

In general situation $\eta \neq 1$, equation $f_\lambda(z) = z$ have solutions

$$z_{1,2} = \frac{-(1+\eta) \pm \sqrt{(1+\eta)^2 - 4d^2\eta}}{2d\eta} = \frac{-\cos(\lambda b_2 x_2) \pm \sqrt{\cos^2(\lambda b_2 x_2) - d^2}}{de^{i\lambda b_2 x_2}}. \tag{53}$$

Note that

$$\text{if } d^2 < \cos^2(\lambda b_2 x_2) < 1 \text{ then } |z_1| < 1,\ |z_2| > 1 \text{ and } z_1 \cdot \overline{z_2} = 1 \tag{54}$$

$$\text{if } \cos^2(\lambda b_2 x_2) \le d^2 \text{ then } |z_1| = |z_2| = 1, \tag{55}$$

and $z_1 = z_2$ if $\cos^2(\lambda b_2 x_2) = d$.

Note that if (52) is satisfied then the Lyapunov function is given by (29), $F(\lambda) = (\rho + 1)\cos^2(\lambda b_2 x_2) - \rho$. The inner points of the allowed bands $\bigcup_{n=1}^\infty b_n$ satisfy $|F(\lambda)|^2 < 1$ which is equivalent to $d^2 < \cos^2(\lambda b_2 x_2) < 1$. On the spectral gaps $\bigcup_{n=1}^\infty g_n$ we have $\cos^2(\lambda b_2 x_2) < d^2$. The non-generated edge point of a band is given by $\cos^2(\lambda b_2 x_2) = d^2$. The degenerated edge point λ_0 satisfy $\cos^2(\lambda b_2 x_2) = 1 \Leftrightarrow \lambda_0 = \pi m / b_2 x_2$.

Hence we get the following version of the forth result in Theorem 2:

Proposition 2. *If $\lambda \in \bigcup_{n=1}^\infty g_n$ then the linear fractional automorphism f_λ has two fixed points z_1, z_2 of hyperbolic type: $|z_1| = |z_2| = 1$. The sequence r_k converges to r as $k \to \infty$, where*

$$r = \lim_{k\to\infty} f_\lambda^{[k]}(r_1)$$

is either z_1 or z_2.

If λ is a non-degenerated band edge point: $F(\lambda) = \pm 1$ and $F'(\lambda) \neq 0$, then f_λ has one (double) fixed point $z_1 = z_2$ and $|z_1| = 1$.

We have

$$r = z_1 = \lim_{k\to\infty} r_k = \lim_{k\to\infty} f_\lambda^{[k]}(r_1).$$

If $\lambda = \lambda_0$ is degenerate band edge point $F(\lambda_0) = \pm 1$, $F'(\lambda_0) = 0$ (degenerate band edge) then $r_k(\lambda) = 0$ for all $k = 1, 2, 3 \ldots$.

The Proposition is still valid if condition (52) is not imposed.

Appendix A. Numerical calculations

In this section we present some examples of the resonance spectrum. The resonances are solutions of the equations $D_{2k+1}(-i\lambda) = 0$, where D_n, $n = 2k+1$, are defined iteratively by (33), Section 4. The zeros of $D_{2k+1}(-i\lambda)$ are calculated numerically by using the Newton procedure. Using Matlab we plot the resonance spectrum for the number of identical cells $k = 3, 4, 5$. In the same figure we show the band spectrum for the corresponding periodic problem satisfying (4). The small circles on the real axis marks the position of $\lambda_0 = \pi m/(x_2 b_2)$ when the one-cell system is perfectly transparent: $|t_1(\lambda_0)|^2 = 1$, $|r_1(\lambda_0|^2 = 0$.

On Figure (1) condition (6) is satisfied: $b_1 = 1,\ b_2 = 4,\ x_2 = 0.2$.

On Figure (2) condition (6) is not satisfied: $b_1 = 1,\ b_2 = 3.8,\ x_2 = 0.2$.

On Figure (3) condition (6) is not satisfied: $b_1 = 3.8,\ b_2 = 1,\ x_2 = 0.8$.


PROFILE OF a(x)
1
0.8
0.6
0.4
0.2
0
−1
0
1
2
3
4


RESONANCES FOR P_k AND BAND SPECTRUM FOR P
0
−0.05
−0.1
−0.15
−0.2
−0.25
7
8
9
10
11
12
13


PROFILE OF a(x)
1
0.8
0.6
0.4
0.2
0
−1
0
1
2
3
4
5


RESONANCES FOR P_k AND BAND SPECTRUM FOR P
0
−0.05
−0.1
−0.15
−0.2
−0.25
7
8
9
10
11
12
13


PROFILE OF a(x)
1
0.8
0.6
0.4
0.2
0
−1
0
1
2
3
4
5
6


RESONANCES FOR P_k AND BAND SPECTRUM FOR P
0
−0.05
−0.1
−0.15
−0.2
−0.25
7
8
9
10
11
12
13


PROFILE OF a(x)
0
0.2
0.4
0.6
0.8
1
−1
0
1
2
3
4


RESONANCES FOR P_k AND BAND SPECTRUM FOR P
0
−0.05
−0.1
−0.15
−0.2
−0.25
7
8
9
10
11
12
13


PROFILE OF a(x)
0
0.2
0.4
0.6
0.8
1
−1
0
1
2
3
4
5


RESONANCES FOR P_k AND BAND SPECTRUM FOR P
0
−0.05
−0.1
−0.15
−0.2
−0.25
7
8
9
10
11
12
13


PROFILE OF a(x)
0
0.2
0.4
0.6
0.8
1
−1
0
1
2
3
4
5
6


RESONANCES FOR P_k AND BAND SPECTRUM FOR P
0
−0.05
−0.1
−0.15
−0.2
−0.25
7
8
9
10
11
12
13


PROFILE OF a(x)
1
0.8
0.6
0.4
0.2
0
−1
0
1
2
3
4


RESONANCES FOR P_k AND BAND SPECTRUM FOR P
0
−0.02
−0.04
−0.06
−0.08
−0.1
−0.12
−0.14
−0.16
−0.18
−0.2
7
8
9
10
11
12
13


PROFILE OF a(x)
1
0.8
0.6
0.4
0.2
0
−1
0
1
2
3
4
5


RESONANCES FOR P_k AND BAND SPECTRUM FOR P
0
−0.02
−0.04
−0.06
−0.08
−0.1
−0.12
−0.14
−0.16
−0.18
−0.2
7
8
9
10
11
12
13


PROFILE OF a(x)
1
0.8
0.6
0.4
0.2
0
−1
0
1
2
3
4
5
6


RESONANCES FOR P_k AND BAND SPECTRUM FOR P
0
−0.02
−0.04
−0.06
−0.08
−0.1
−0.12
−0.14
−0.16
−0.18
−0.2
7
8
9
10
11
12
13

References

[1] C. Cohen-Tannoudji and B. Diu and F. Laloë. *Quantum Mechanics*. New York: Wiley, 1977.
[2] B.M. Levitan and I.S. Sargsyan. *Sturm-Lioville and Dirac Operators*. Moscow, 1988 (in russian).
[3] F. Barra and P. Gaspard. Scattering in periodic systems: from resonances to band structure. *J. Phys. A: Math. Gen.*, 32:3357–3375, 1999.
[4] Valeria Banica. Dispersion and Strichartz inequalities for Schrödinger equations with singular coefficients. *SIAM J. Math. Anal.*, 35(4):868–883, 2003.
[5] R. B. Burckel. Iterating analytic self-maps of discs. *The American Mathematical Monthly*, 88(6):396–407, 1981.
[6] David J. Griffiths and Carl A. Steinke. Waves in locally periodic media. *Am. J. Phys.*, 69(2):137–154, 2001.
[7] B. Vainberg S. Molchanov. Slowing down and reflection of waves in truncated periodic media. *J.Func.An.*, 231:287–311, 2006.

Malmö University, School of Technology and Society, SE-205 06 Malmö, Sweden
E-mail address: `ai@ts.mah.se`